

PEDAL PUSHER



Shown with Dante option.

Dual mono Console/DAW to Guitar Pedal Interface

- Each channel features:
 - High headroom line level balanced input to efx pedal send with impedance and level matching.
 - High impedance guitar pedal return to high headroom line level balanced output.
 - Selectable pickup simulation, Active or Passive.
 - High frequency equalizer in the passive position to simulate or negate the effect of guitar cable.
- Low noise universal power supply built in, no wall wart!
- Six isolated, high current power supplies, each with four selectable voltages for low noise pedal power.
- Pedal Returns can also function as high quality, dual mono or stereo, high impedance, direct instrument inputs (DI) with line level outputs. Each return has two gain settings.
- Pedal Sends can serve as high quality outputs from a console/DAW to a guitar amp for re-amp use.
- Routing switches add flexibility for feeding both loops from one input or both outputs from one Pedal return. For example: feed two different pedal loops from a single line input or feed a clean and effected signal to the console from a guitar input.
- DANTE option allow connection to Dante network at sample rates up to 96k. Outputs are mirrored at analog outputs. Inputs are selectable from Dante or analog.

AudioSimplified

Pedal Pusher Specs:

Line Inputs:

Nominal Level : +4dBu
Maximum Input level: +24dBu
Impedance: 48k Ω differential

Line Outputs:

Nominal Level : +4dBu
Maximum Balanced Output level: +27.5dBm into 600 Ω
Maximum UnBalanced Output level: +22dBm into 600 Ω
Frequency Response:
20Hz to 20kHz +0.02dB, -0.12dB

Noise level:

-101.3 dBa

Distortion:

THD: .00114%
IMD: .00278%

Power:

Voltage Range: 80-246vac (universal power)
Frequency Range: 47-63Hz
A/C Current: 1.5A @115VAC

Isolated DC Supplies:

500ma@9V each output
voltages available: 9v, 12v, 18v, 24v

Dimensions:

width: 14.75" (375mm)
height: 1.75" (42mm)
depth: 4" (100mm)

Dante Option:

Sample Rates: All standard up to 96k
Ports: 2 (to function as daisy chain)
Outputs: Dante and analog simultaneously
Inputs: Dante or analog switchable

Price:

Pedal Pusher: \$450.00
Rack Ears option: +\$18.00
Pedal Pusher with Dante: \$600.00

©2021 Audio Simplified LLC Jim Mikles
6401 Hickory Overlook, Columbia, MD 21044
audio-simplified.com 410.999.0918